80mm

120mm

MOES
HOME, SMART MOES HOME
Powered by tuya

Instruction Manual Smart Switch

Wi-Fi+RF433

EU US

English

WORKS WITH Google Assistant
WORKS WITH alexa

WRS-EU-MS-DB26

- Bitte scannen Sie den QR-Code, um das deutsche Handbuch, das Installationsvideo und die Funktion seinführung zu erhalten
- Escanee el código QR para obtener el manual en español, el vídeo de instalación y la introducción de la función
- Veuillez scanner le code QR pour obtenir le manuel en français, la vidéo d'installation et l'introduction des fonctions
- Отсканируйте QR-код, чтобы получить руководство на русском языке, видео по установке и описание функций
- Scansionare il codice QR per ottenere il manuale in italiano, il video di installazione e la guida alle funzionalita. Video di installazione e funzionalita
- Leia o código QR para obter o manual em português, o vídeo de instalação e a introdução das funções
- Zeskanuj kod QR, aby uzyskać instrukcje, filmy instalacyjne i funkcje
- من فضلك قم بمسح رمز الاستجابة السريعه(QR-code)للحصول على دليل المستخدم باللغة العربية وفيديو التثبيت ووصف للوظائف

请扫描二维码获取说明书手册、安装视频和功能介绍

Product Description

This new designed glass panel wireless touch smart **switch is designed with WiFi+RF to replace traditional** switches with a variety of ways to control.Now one new smart feature as multi-control association to other smart **switches is added into the MOES App.together with the** backlight on/off and relay status.And its scratch resistance glass panel is suitable for different decoration styles with its best value.
Note: Button sound on and off: no button operations before operations begin within 6 seconds.Then press switch button for 4 times and long press for the fourth time until the switch beep sounds as Di-Di for 2 times for successful operation.

Safety Information

Risk of Electric Shock:Electricity can cause personal injury and property damage if handled improperly.If you are not sure about any part of these instructions,please seek professional assistance from a qualified electrician.

Technical Parameters:

Model: WS-EU-RF / WS-US-RF
Voltage: 90~250V AC, 50/60Hz
Max. Current: 10A/Gang; Total 10A
Wireless Protocol: Wi-Fi 2.4GHz+RF433MHz
Frequency Band: 2.412 ~ 2 . 484GHZ
Maximum Radio Transmit Power: < + 16dbm

Warnings:

Turn off the power at the circuit breaker and test that power is off before wiring.

Installation

Note:
- Make sure that the power at the circuit breaker is off before wiring.
- Neutral Wire is required.Confirm the wall box contains a Neutral Wire(typically white).If the wall box don't have a Neutral Wire,please try another location at your home or call a professional electrician to install the switch.
- The wire colors indicated in this manual are the usual colors and may differ in some houses.
- Ensure the wire conductors are securely fastened to each wire.
- Ensure the Wi-Fi signal is steady and normally working before wiring.
- If you don't have any wiring experience,please call a professional electrician.

Step 1
- Turn off the circuit breaker and use the electrical tester to test the power.
- Ensure the circuit breaker is off before wiring.



⚠ Attention:
Please disconnect the power supply before installing or removing the device for avoiding irreversible damage on the device from the electric current or some unpredictable problems such as lamp flashing.

Step 2
- Remove the old switch



Step 3
- Remove the switch and pull it away from the wall. Identify Line/Load Wire(Note:The color of your wire may be different from the color shown on the manual.)

⚠ Verify power is off
- We recommend you remove the faceplate from the old switch and use an electrical tester to test all wires connected to the switch to ensure there is no voltage in the circuit.
- You may need to turn off more than one circuit breaker.

Step 4
- Take pictures of the wiring



- Follow the wiring diagram to connect the switch wires to the wires in the wall box with the wire conductors.

Step 5
- Remove the panel with screwdriver **(Please don't install with electricity power on)**

Step 6
- **Prepare to install wiring**
  A. Live wire connects " L " terminal
  B. Neutrail wire connects " N " terminal
  C. Lamp wire connects " L1,L2,L3,L4 " terminal
  1 Gang connects "L1" terminal
  2 Gang connects "L1,L2" terminal
  3 Gang connects "L1,L2,L3" terminal
  4 Gang connects "L1,L2,L3,L4" terminal

1-3 Gang



4 Gang





Step 7
- Put the switch into switch box in the wall
- Mount the two side screws
- Install the glass panel (install from up above)
- Finish installation



Preparation for use

1 Download MOES App on App store or scan the QR code

GET IT ON Google Play
Download on the App Store

MOES App is upgraded as much more compatibility than Tuya Smart/Smart Life App,functional well for scene controlled by Siri,widget and scene recommendations as the fully new customized service.
(Note: Tuya Smart/Smart Life App still works,but MOES App is highly recommended)

2 Registration or Log in

- Download "MOES" Application.
- Enter the Register/Login interface; tap "Register" to create an account by entering your phone number to get verification code and "Set password". Choose "Log in" if you already have a MOES account.

Steps for connecting the APP to the device

Method One:
1. Make sure your phone is connected to Wi-Fi and Bluetooth.

Figure 1

2. Scan the QR code to configure the network guide.

① Figure 2 ② Figure 3

Scan the QR code

Please connect the device according to the configuration process.

Figure 4 Figure 5

Method Two:
1. Make sure your phone is connected to Wi-Fi and Bluetooth.

Figure 6

2. Press and hold the button for about 6 seconds,until the blue indicator on the switch flash fast after 3 seconds. Reset/Repair is successful.

3. Open the MOES App, click the "+" in the upper right corner, enter "Add Device", the device will appear in "discovering devices", click "Add".

Figure 7

Add Device
Smart Switch
Add Manually
Socket
Lighting
Plug
(BL)
(BL)
Socket
(BL)
Power Socket
(BL)
Switch
(BL)
Curtain Switch
(BL)
Smart Switch
(BL)
Gateway (BL)
Temperature and Humidity Sensor
(BLE)
Door Sensor
(BLE)
Motion Sensor
(BLE)
Water Sensor
(BLE)
Smart Siren
(BLE)
Smart Button
(BLE)
Remote Control
(BLE)
Gas Sensor
(BLE)
Smart Lock
(BLE)
Smart Curtain
(BLE)
Smart Thermostat
(BLE)
Smart Thermostat Valve
(BLE)
Smart Light
(BLE)
Smart Socket
(BLE)
Smart Light
(BLE)
Smart Socket
(BLE)
Smart Light
(BLE)
Smart Socket